

### Tip for :Compleo Solo

We recommend the following configuration tips when you try to configure the Smartmaster Pro with a Compleo Solo charger.

1 Open your web browser and type in 192.168.1.100 (Change your IP-address to 192.168.1.101).

---

2 The login number is located inside the terminal.

---

3 In the Ducto webapp, select Ethernet DHCP under Network.

---

4 In the Ducto webapp, place the URL : ws://{SMARTMASTER\_IP\_ADDR}:8834/ocpp under Backend/connection/ Backend URL.

---

5 In the Ducto webapp, place the serial number under ChargeBoxIdentidy (it is located on the right-hand side of the charging station). : Allow local Modbus TCP API into advanced settings.